

DIN Rail DALI Series Dimming Driver



(Please read through this manual carefully before use)

1. Brief Introduction

Welcome to use our DIN Rail DALI Series dimming driver, which input standard DALI signal and adopted the most advanced DALI standard IEC62386. It can meet with any equipment in line with the DALI protocol on a bus control, and realize the LED lighting products and traditional lighting integrate within the same set of lighting system. We also add short circuit protection and over-current protection in the driver, which avoid the LED lamp from being damage.

2. Specifications

1CH DALI Dimming Driver



- Input Voltage: DC12V-24V
- Output Current: 10A×1CH
- Output Power: 120W/240W(12V/24V)
- Working Temperature: -20°C~55°C
- Dimension: L111×W46×H66(mm)
- Weight(G.W): 118g




3CH DALI Dimming Driver

- Input Voltage: DC12V-24V
- Output Current: 8A×3CH Max 24A
- Output Power: 288W/576W(12V/24V)
- Working Temperature: -20°C~55°C
- Dimension: L111×W46×H66(mm)
- Weight(G.W): 122g

— 1 —

6. Wiring Indication

Passive DALI bus signal input wiring diagram a: (no need to distinguish DALI bus is anode or cathode)



7. After-Sales

From the day you purchase our products within 3 years, if being used properly in accordance with the instruction, and quality problems occur, we provide free repair or replacement services except the following cases:

- 1.Any defects caused by wrong operations.
- 2.Any damages caused by inappropriate power supply or abnormal voltage.
- 3.Any damages caused by unauthorized removal, maintenance, modifying circuit, incorrect connections and replacing chips.
- 4.Any damages due to transportation, breaking, flooded water after the purchase.
- 5.Any damages caused by earthquake, fire, flood, lightning strike etc force majeure of natural disasters.
- 6.Any damages caused by negligence, inappropriate storing at high temperature and humidity environment or near harmful chemicals.
- 7.Product has been updated.

— 3 —

4CH DALI Dimming Driver



- Input Voltage: DC12V-24V
- Output Current: 6A×4CH Max24A
- Output Power: 288W/576W(12V/24V)
- Working Temperature: -20°C~55°C
- Dimension: L111×W46×H66(mm)
- Weight(G.W): 122g



5CH DALI Dimming Driver

- Input Voltage: DC12V-24V
- Output Current: 5A×5CH Max25A
- Output Power: 300W/600W(12V/24V)
- Working Temperature: -20°C~55°C
- Dimension: L111×W46×H66(mm)
- Weight(G.W): 124g


3. Basic Features

1. Automatically adapts input voltage DC12V-24V.
2. Can meet with any equipment in line with the DALI protocol on a bus control.
3. With the DALI signal input optical isolation protection.
4. Over current protection and short circuit protection.
5. The DIN rail style facilitates the installation of large-scale projects.

4. Safety warnings

1. To ensure your safety and product properly usage, please read the user manual carefully.
2. To avoid installed the product in minefield, strong magnetic field and high voltage area.
3. To ensure the wiring is correct and firm avoiding short circuit damages to components and cause fire.
4. Please install the product in a well ventilated area to ensure appropriate temperature environment.
5. The product must be worked with DC constant voltage power supply. Please check the consistence of input power with the product, if the output voltage of the power comply with that of the product.
6. Connect the wire with the power on is forbidden. Ensure proper wiring first then check to ensure no short-circuit, then power on!
7. Don't repair it by yourself whenever an error occur. Contact the supplier for any inquiry.

5. Dimensions



— 2 —

8. Kindly Reminder

1.Power Source Selection

Power source must be DC constant voltage type of power supply. Due to the efficient output in some power supplies are only 80% of total, so please select at least 20% higher output power supply than the consumption of LED lights.

— 4 —